



by Honeywell

600 Series IdentiFlex 602 with SmartScan™

Description

The IdentiFlex 602 (IF602SS) with SmartScan™ is ideally suited for small- to medium-sized installations at commercial, institutional, and industrial life-safety projects.

The IF602SS has all the features of today's most advanced life safety systems. The integration of analog and addressable hardwired circuits allows system engineers to customize panels and maximize efficiency for any application.

The IF602SS can monitor and control up to 396 intelligent analog addressable input/output points. The interactive operator's display uses LED prompting for ease of programming and user operation. The alphanumeric display and keypad simplify field programming, or download programming from a Windows®-based application.

The IF602SS's housing will fit between 16" studs for semi-flush mounting. Access to system function keys is limited by a key switch. Multiple levels of password protection prohibit unauthorized use. The circuit boards are mounted on a removable chassis with pluggable terminal strips for ease of installation and service.

Operator's Display

The IF602SS's operator's display controls all user access to the system. The display provides all of the necessary keys and annunciation points to maintain and monitor the system. Alarm, supervisory, and trouble conditions are all indicated on the operator's display by dedicated LEDs and an internal sounder. The Acknowledge, Reset, and Signal Silence keys are located directly below the 4 x 40-character backlit alphanumeric display. All system functions and operational logic can be programmed from the front panel in the field. The IF602SS display has four user-programmable function keys.

Analog Addressable Signaling Line Circuits

The IF602SS analog interface module provides Signaling Line Circuits (SLC), loop circuits that can monitor and control up to 198 analog/addressable devices on each power-limited loop, for a total of 396 analog points in a dual-loop system. Loop wiring is polarity sensitive.

SmartScan™ Series and SmartStart™ are trademarks of Honeywell International Inc. Microsoft® Windows® is a registered trademark of Microsoft® Corporation.

Analog Addressable Control Panel



Features

- One or two Signaling Line Circuits (SLC), up to 396 points.
- SmartScan™ protocol 99 detectors, 99 devices per WP.
- SmartScan™ self-programming logic.
- Downloadable or front-panel programmable.
- Password protected.
- Approved for Agent Releasing and Supervisory Service.
- Fully digital SLC protocol.
- SmartLink™ peer-to-peer networkable.
- 1000-event history log.
- Automatic drift compensation.
- Coded signaling capability.
- Adjustable sensor sensitivity and temperature settings.
- Supervisory service.
- Style 6 (Class A) or Style 4 (Class B) SLC.
- Four Style Y (Class B), or two Style Z (Class A) notification appliance circuits (NACs).
- Semi-flush mounting (between 16" studs).
- 160-character display.
- Optional UDACT.
- Built-in strobe and horn synchronization.

An ISO 9000-2000 Company



GAMEWELL-FCI

12 Clintonville Road, Northford, CT 06472-1610 USA • Tel: (203) 484-7161 • Fax: (203) 484-7118

Specifications are for information only, are not intended for installation purposes, and are subject to change without notice. No responsibility is assumed by Gamewell-FCI for their use.

Each SLC loop has a dedicated microprocessor that simultaneously communicates with connected field devices and the main CPU.

The IF602SS uses SmartScan™ fully digital communications protocol to improve the speed and accuracy of event reporting. The communications protocol provides for alarm verification per detector, detector adjustability and compensation, adjustable analog heat detector range circuit isolation, and priority interrupts. Priority interrupts allow contact-type devices such as manual fire alarm stations to interrupt the polling cycle and transmit their addresses at any time during a polling sequence.

The fully digital protocol allows the IF602SS to operate on most types of field wiring, greatly expanding its use in retrofit applications. Consult the supplemental SLC manual on tech support for specific wiring requirements.

IF602SS Power Supply

The IF602SS power supply is a fully regulated 8 Amp supply that furnishes system operating and signaling power. It is equipped with a battery charger which maintains the secondary power source. The power supply is monitored by the main CPU, ensuring that adequate power levels are available. The power supply design allows for high efficiency while providing precise power output. The battery charger maintains batteries up to 26 AH. The supply powers four on-board Notification Appliance Circuits (NACs) (two Class A) with multiple built-in synchronization protocols for System Sensor, Cooper-Wheelock and others.

Input (I) / Output (O) Devices

Addressable control output devices are the interface between analog circuits and building functions. The outputs are controlled with Control By Event (CBE) software within the IF602SS, and can be programmed to respond to any event. The control devices can be used as supervised remote signaling circuits.

The IF602SS, with Gamewell-FCI's complete line of 600 Series devices, provides a foundation for system design. The IF602SS's RS-232 output expands system monitoring and control capabilities.

Remote Display and Control

Serial annunciator drivers are available in 16-point increments and are an ideal interface to graphic annunciators. Switches can be used for Acknowledge, Reset, Signal Silence, Drill, etc., to customize the remote status control network.

An alphanumeric display can also be used for remote status and control. The alphanumeric display is designed to communicate over the serial communications network.

The IF602SS can communicate locally or remotely with a printer to document system activity.

See the RAN/SAN data sheet (CS-2025) for complete annunciator details.

Applications

The IF602SS Analog Addressable Control Panel is designed for new or retrofit small- to mid-sized projects that require state-of-the-art life-safety systems. The embedded CPU offers users unrivaled reliability without sacrificing flexibility or value.

With compatible analog sensors and addressable input and control interface devices, and its remote status and control capabilities, the IF602SS provides system engineers with all the tools necessary to design effective system solutions for any application.

Architectural/Engineering Specifications

The control panel furnished and installed shall be capable of supporting 396 addressable devices and two analog loops. The panel shall utilize a fully digital Signaling Line Circuit (SLC) protocol. The panel shall contain four on-board Notification Appliance Circuits (NACs) that support multiple synchronization protocols. The panel shall utilize a 160-character Liquid Crystal Display (LCD) and a 1,000-event history log. The panel shall be a Gamewell-FCI IF602SS with SmartScan™.

GAMEWELL-FCI

Specifications

Common Control:

Standby Current: 0.125A
Alarm Current: 0.171A plus signaling circuit power, plus 0.002A for master box, or plus 0.022A for reverse-polarity
Input Power: 120 VAC, 3.0A; or 240 VAC, 1.5A

Auxiliary Output:

S+/S-, A+/A-: 2.0 A maximum
Common Relays: 1.0A @ 30 VDC, or 0.5A @ 250 VAC

Notification appliance circuits:

Circuits: Four Class B, two Class A.
Output: 3.0A maximum @ 24 VDC per circuit. Maximum 8.0A total for all circuits.

Analog SLC: **198** **396**
Standby Current: 0.045A 0.055A
Alarm Current: 0.045A 0.055A

Panel Dimensions:

Standard Cabinet: 20.0" H x 14.0" W x 4.5" D
(50.8 H x 35.6 W x 11.4 D cm)
XL Cabinet: 30.0" H x 22.0" W x 5.5" D
(76.2 H x 55.9 W x 13.97 D cm)

Battery Storage Dimensions:

Standard Cabinet: 6.0" H x 9.0" W x 4.5" D
(15.24 H x 22.86 x 11.43 D cm)
XL Cabinet: 14" H x 22.0" W x 5.5" D
(35.56 H x 55.88 W x 13.97 D cm)
Relative Humidity: 93% non-condensing
Temperature Rating: 32°F – 120°F (0°C – 49°C)

Ordering Information

Model	Description
IF602SS-198R	IF602SS Analog Addressable System with SmartScan™ consisting of the following: <ul style="list-style-type: none">• IF602SS common control.• 8 amp main power supply.• One (1) analog circuit module (198 analog addressable points).• Standard cabinet assembly (CAB-602R). Standard Cabinet: 20.0" H x 14.0" W x 4.5" D (50.8 H x 35.6 W x 11.4 D cm)
IF602SS-198XL	198 point/one SLC IF602SS in extra-large housing allowing space for battery storage (Refer to IF602SS-198R model listed above). Extra-large Cabinet: 30.0" H x 22.0" W x 5.5" D (76.2 H x 55.88 W x 13.97 D cm)
IF602SS-396R	IF602SS analog addressable system with SmartScan™, consisting of the following: <ul style="list-style-type: none">• IF602SS common control.• 8 amp main power supply.• Two (2) analog circuits module (396 analog addressable points).• Standard cabinet assembly (CAB-602R). Standard Cabinet: 20.0" H x 14.0" W x 4.5" D (50.8 H x 35.56 W x 11.43 D cm)
IF602SS-396XL	396 point/two (2) SLC IF602SS (refer to IF602SS-396R above) in extra-large housing, allowing space for battery storage. Extra-large Cabinet: 30.0" H x 22.0" W x 5.5" D (76.2 H x 55.88 W x 13.97 D cm)
72214	Identiflex 602 Installation and Operation Manual
31077	CTM-602, city-tie/remote signaling module for 602 Series panels.
31078	ISO-232, RS-232 serial-port isolator module for 602 Series panels.
31079	CLA-602, Class "A" adapter module for SLC, 602 Series panels.

GAMEWELL-FCI

12 Clintonville Road, Northford, CT 06472-1610 USA • Tel: (203) 484-7161 • Fax: (203) 484-7118

www.gamewell-fci.com

CS-2490 Rev. A page 3 of 3